



KVMA switch to share Video and USB between multiple sources

## ADDERView 4PRO-DVI

Ultimate flexibility for sharing high-res screens and USB peripherals



### PRODUCT IN BRIEF

The AV4PRO-DVI is designed to enable four computers to be controlled from a single high resolution KVM console using either dual link DVI or high definition analogue video links. The switch makes use of Adder's True Emulation technology which enables USB HID devices to be continuously emulated to each computer. This unique technology enables instantaneous and reliable hot-key switching whilst also supporting the extra keys and features of enhanced keyboards and mice. Furthermore, the AdderView includes two independently switchable USB 2.0 channels and an audio channel, giving the user the flexibility to attach selected peripherals to different computers.

Examples of switching flexibility on the AV4PRO-DVI. Diagrams show the switching of connected devices across all connected computers and the selection of all connected devices to a single computer.



Independent simultaneous device selection

Switching all connected devices to a single computer

### FEATURES

#### Dual link DVI-I with extended profile DDC EDID

The AdderView Pro features full dual link DVI video delivering 4 megapixel resolutions at 60Hz. Because the AdderView features DVI-I, you can also use a choice of digital or analogue sources. The extended DDC EDID profile ensures that the switched graphics card is always optimised to work with your screen. The dual link DVI capabilities enable users to work at very high resolutions including 2K (2048 x 1080) for film post production or WQXGA (2560 x 1600) for detailed medical imaging.

#### True Emulation USB2.0 technology

The AV4PRO-DVI belongs to the first KVMA range of switches to feature Adder's advanced True USB Emulation technology. Emulated USB provides an instantaneous and reliable switching action and makes keyboard hotkey and mouse switching possible. However, previous implementations have used only generic emulations and consequently have only been able to support the most basic keyboard and mouse features. Adder's revolutionary True Emulation technology overcomes this frustrating limitation by emulating the true character of the connected devices to all the computers simultaneously. This means that you can now use the extra function keys, wheels, buttons and controls that are commonly found on modern keyboards and mice.

#### Independent simultaneous device selection

Flexibility is key to the AdderView Pro. The switch enables you to use the KVMA console to work on one computer whilst your USB peripherals are connected to other computers

and your speakers are playing music from yet another. You can of course still switch all connected devices to any one of the connected computers as with any other KVM switch.

#### Channel selection options

The AdderView Pro can be switched using selectable keyboard hotkeys, 3 button mice or the front panel controls. Optionally, you can also use the RC4 remote switch to make your selection. These switching options allow you to rapidly reassign connected devices to any of the connected computers.

#### Broad USB 2.0 Hi Speed device support

A vast range of USB devices can be connected to the AdderView. From non standard human interface devices to printers and scanners. This gives great flexibility. For example, you could be scanning a set of documents onto one computer whilst working on another and printing from yet another, all at the same time. The USB 2.0 switching action has been carefully engineered to ensure maximum computer reliability when connecting and disconnecting USB devices.

#### Options port for control, synchronisation and upgrade

An 'Options' port enables the AV4PRO-DVI to be remotely switched using simple ASCII codes. When the channel is switched, the same ASCII codes are echoed to the 'Options' port and so, by linking 'Options' ports, two or more units can be switched in synchrony to create a multi video head switching system. The port enables a 4 button switch unit (RC4) to be used with the AdderView Pro. The same port can also be used to upgrade the firmware to guarantee that your hardware investment continues to deliver real value well into the future.

# ADDERView 4PRO-DVI

Ultimate flexibility for sharing high-res screens and USB peripherals

## ABOUT ADDER

Adder is a leading developer and thought leader in connectivity solutions. Adder's advanced range of KVM switches, extenders and IP solutions enable the control of local, remote and global IT systems across the enterprise. The company distributes its products in more than 60 countries through a network of distributors, resellers and OEMs. Adder has offices in the United States, United Kingdom, Germany, the Netherlands, Sweden, China and Singapore.

To find out more, visit:  
<http://www.adder.com>.

## TECHNICAL SPECIFICATIONS

### Hardware compatibility

Supports PC, RS/6000, Alpha, SGI, Sun and Apple with USB keyboard and mouse, and VGA or DVI video interfaces

### Software compatibility

Operates with all known software and operating systems including Windows (all), DOS, Linux, Unix, BSD, all Sun OS, all Mac OS, NetWare etc.

### Computer connections at switch

USB2.0 type B, Dual-link DVI-I, 3.5mm stereo jack

### Local KVM console connection Video:

- Video: Dual-Link DVI-I
- Keyboard/Mouse: 2 x USB type A
- Switched USB: 2 x USB2.0 type A
- USB True Emulation: Emulates keyboard and mouse on each port. Low speed HID USB 2.0 devices supported
- Audio: 3.5mm stereo jack
- Other Connections: Options (flash upgrade, sync with other AV4PRO-DVI and RS232 triggered power switches): Modular IOP10C

### Physical design

1U high metal case 233mm (w), 115mm (d), 44mm (h)

### Power

2.5mm DC jack (power adapter included), 100-240VAC 50/60Hz input to

## ORDERING INFORMATION

AdderView PRO 4 port switch: **AV4PRO-DVI-XX**

XX = Mains Lead Country Code:  
UK = United Kingdom  
US = United States  
EURO = Europe  
AUS = Australia

## ADDITIONAL ACCESSORIES

Rack Mount Kit: **RMK3**  
DVI to VGA adaptor: **VSA11**  
Single link DVI-D to DVI-D Video cable: **VSCD1**  
Audio cable 2 m: **VSC22**  
Combined dual link DVI-D and USB cable:  
**VSCD3 (2m); VSCD4 (5m)**  
Flash upgrade adapter plus standard 3 m patch lead:  
**VSC40**  
RC4 remote control plus standard 3 m patch cable:  
**RC4-8P8C**

power adapter, 5VDC 2A output from power adapter

### Operating temperature

0°C to 40°C / 32°F to 104°F

### Approvals

CE, FCC

## RELATED PRODUCTS

Adder offer a vast range of products to suit your needs. Other products you may be interested in include:

**ADDERView PRO**  
AV8PRO-DVI



**ADDERView PRO MultiScreen**  
AV4PRO-DVI-DUAL;  
AV4PRO-DVI-TRIPLE;  
AV4PRO-DVI-QUAD



**SmartView MultiScreen DVI**  
SVMS2DVI-DUAL,  
SVMS2DVI-QUAD,  
SVMS4DVI-DUAL,  
SVMS4DVI-QUAD



**ADDERView Secure**  
AVS2007; AVS4007



© Copyright 2010 Adder Technology Ltd. All brand names and trademarks are the property of their respective owners. AH-av4pro\_dvi\_v1.ID