

# Features

- 4K UHD HDMI EDID Feeder with Splitter Function (HDCP Engine built in)
- Allow to restore 4 customized EDID information
- Avoid computer from deactivating or inactive HDMI ports
- Copy EDID from the connecting display
- Economical, durable and dependable
- EDID Ghost (DDC Ghost)
- Support over 100 popular resolution

# Highlight Feature

- Emulator maximum supports up to 4K UHD@30Hz 3840 x 2160 Resolution
- Built in EDID/HDCP Engine
- Built in Splitter Function
- Incorporate EDID and HDCP handling procedures for continuous video output
- Auto configuring EDID from the connecting display, Easy and Ready to Go

Model Type	VDDC-400HDMI
Input	HDMI x 1
Output	HDMI x 2 (Main x1, Aux x1)
HDCP Engine	Yes
Resolution (Max.)	3840 x 2160@30Hz
Status LED	x 2 Dual Color (Blue & Green)
Power Supply	5V DC (mini-USB)
Housing	Metal
Dimensions (H x W x D)	24 x 98 x 64 mm
Weight (g)	200

EDID Source Table

1. Auto Learn (M)	From Main Port Monitor
2. Auto Learn (A)	From Aux Port Monitor
3. Inventory EDID	Customized EDID x 4

